

Settings	Description	Account	Group	Filter	Device
<b>Add Custom Values</b>	Create custom data fields to store additional information about a device e.g., location (kitchen vs. floor)	X	X	X	X
<b>Admin Password</b>	Use to gain restricted access to EloView Control Panel on the Elo device. User cannot update the device (OS), access advanced Android Settings.	X	X	X	X
<b>Allow Content Downgrade</b>	Allow/Disallow Content downgrade	X	X	X	X
<b>Android Home</b>	Displays the standard Android UI	X	X	X	X
<b>Android Nav Bar</b>	Allows access to the app drawer so merchant can navigate to different apps deployed on device.	X	X	x	X
<b>Auto Accept NFC and Camera Usage</b>	Enable/Disable the auto accept usage for NFC and Camera.	X	X	X	X
<b>Auto Correct</b>	Enable/Disable Auto Correct	X	X	X	X
<b>Auto Play</b>	Enable/Disable automatic installation of apps via a USB key placed in the device's USB port. This option is enabled by default - but is disabled when a device is added to an account.	X	X	X	X
<b>Brightness</b>	Edit brightness on device	X	X	X	X
<b>Camera Shortcut</b>	Enable/Disable the double-press shortcut that opens the camera.	X	X	X	X
<b>Content Pinning</b>	When enabled, applications that are running in the background will never replace the content playing on the screen.	X	X	X	X
<b>Control Panel Password</b>	Use this password to gain full (admin) access to EloView Control Panel on the Elo device.	X	X	X	X
<b>Delayed Content Deployment</b>	If enabled, any new content dropped on device, group, filter, or Org will be downloaded and installed at selected time only. It will work on device version >1.0. If disabled, then in that case it will download and install content instantly.	X	X	X	X
<b>Device Mode</b>	Set EloView device modularity. (Core, Connect, Control)	X	X	X	X
<b>Device Screenshot</b>	View current screenshot of device (Settings in "Info" section of EloView device details. Can Enable/Disable or capture "High Quality Screenshot"	X	X	X	X
<b>DFS</b>	Allows you to manually toggle Dynamic Frequency Selection (DFS) on the device. This feature is only supported on iSeries 2.0, 3.0 (AOSP & GMS) devices and 4.0 (Perf & Value).	X	X	X	X
<b>Display Timer On/Off</b>	Sets timer on display to turn on and off each day. The "on" time will turn on the device display. The "off" time will turn off the device display.	X	X	X	X
<b>Enterprise Reset</b>	Resets data on the device	X	X	X	X
<b>EST</b>	Enrollment over Secure Transport (EST) describes a simple, yet functional, certificate management protocol targeting Public Key Infrastructure clients that need to acquire client certificates and associated Certification Authority certificate. See RFC 7030	X	X	X	X
<b>GPS Co-ordinate</b>	Establish GPS Coordinates for a device. (This setting is in "Info" section)				X
<b>Home Button</b>	Allows the physical Home button on the Elo device to behave as intended in Android i.e., display the app drawer.	X	X	X	X
<b>Inbuilt Barcode Scanner</b>	Enable/Disable the device barcode scanner.	X	X	X	X
<b>Interactive Overlay</b>	Adds a navigation bar with a home and back button	X	X	X	X
<b>Language</b>	Set Language of device. Languages available: English, Chinese, French, German, Italian, Japanese, Spanish	X	X	X	X
<b>Microphone</b>	Enable/Disable the device Microphone.	X	X	X	X
<b>Mobile Data</b>	Enable/Disable the device mobile data.	X	X	X	X
<b>Multiple App Mode</b>	When enabled, the device can run multiple apps at once. If disabled, device will run one app at a time (kiosk mode)	X	X	X	X
<b>Nav Bar Color</b>	Change color of Android Navigation Bar (available after Android Nav Bar is enabled)	x	x	x	x
<b>Network Configuration</b>	Enable/Disable Network configuration	X	X	X	X
<b>NTP URL</b>	Use to override Android default NTP configuration. Can accept local or remote NTP server URL or IP[:port]. Device will reboot to apply changes.	X	X	X	X
<b>Orientation</b>	Device orientation - Landscape or Portrait	X	X	X	X
<b>Power Button</b>	Allows the physical Power button on the Elo device to behave as intended in Android i.e., shut down the device.	X	X	X	X
<b>Physical Analytics</b>	Allows device to collect analytics data to determine application effectiveness as measured by impressions vs. touches. This information is displayed in the EloView Dashboard.	X	X	X	X
<b>Quick Settings Access - WiFi/Bluetooth</b>	For 4.0 devices, WiFi and Bluetooth settings can be accessed without entering Admin password				
<b>Reboot</b>	Reboots the device	X	X	X	X
<b>Show Stock Apps</b>	Displays all default Elo Apps and Android apps in the EloView Control Panel. For devices below Android 10, it is recommended to Enable "Android Navigation bar" along with "Show Stock Apps" to access app from app drawer.	X	X		X
<b>Software Update</b>	Update the device software	X	X	X	X
<b>TeamViewer (Remote Control)</b>	Allows remote access to device using TeamViewer (Requires TeamViewer Account)	X	X	X	X
<b>Time Zone</b>	Need to establish, especially for logging purposes	X	X	X	X
<b>Touch Sound</b>	Enables sound when tapping/typing on the device	X	X	X	X
<b>Trigger Button (Left &amp; Right)</b>	Enable or Disable trigger buttons on devices equipped with triggers (M50/M60)	X	X	X	X
<b>Virtual Keyboard</b>	Enables the virtual keyboard for use on the device	X	X	X	X
<b>Volume</b>	Edit volume on device	X	X	X	X
<b>WebView Hardware Access</b>	Enable/Disable the native WebView JavaScript interface for hardware access.	X	X	X	X
<b>Wi-Fi</b>	Enable/Disable WiFi	X	X	X	X